

## PARTS LIST

As of JAN 24 89

PRODUCT: SP14

SP14

## NOTES:

Schematic Symbol	Quantity	ARC Part#	Description
R 9,13,24,27	8	42274405	RES. 27.4K 1% MK-8 50PPM
R 9B	2	42825405	RES. 82.5K 1% MK-8 50PPM
R 11,64	4	42357203	RES. 357 OHM 1% MK-3 50PPM
R 12,62	4	42274103	RES. 27.4 OHM 1% MK-3 50PPM
R 14,26,26A	6	42150414	RES. 15K 1% MK-5 50PPM
R 15,20,28	6	42475503	RES. 475K 1% MK-3 50PPM
R 16,16B,18	6	42619203	RES. .619 OHM 1% MK-3 50PPM
R 17	2	42562513	RES. 562K 1% MK-4 50PPM
R 18A	2	42274403	RES. 27.4K 1% MK-3 50PPM
R 18B	2	42357403	RES. 35.7K 1% MK-3 50PPM
R 21,29	4	42200205	RES. 200 OHM +/-1% MK8 50PPM
R 22,22A	4	42681303	RES. 6.81K 1% MK-3 50PPM
R 24A,24B,27A,35,36,42,43	10	42100505	RES. 100 1% MK-8 50PPM
R 25	2	42332103	RES. 33.2 OHM 1% MK-3 50PPM
R 25A,40,46B	4	42332203	RES. 332 OHM 1% MK-3 50PPM
R 26B,26C	4	42348403	RES. 34.8K 1% MK-3 50PPM
R 30,61	4	42681405	RES. 68.1K 1% MK-8 50PPM
R 31,31A,31B	6	42182303	RES. 1.82K 1% MK-3 50PPM
R 31C	2	42150303	RES. 1.50K 1% MK-3 50PPM
R 32	1	43100202	RES. 100 OHM 2W 5%
R 33	1	42158513	RES. 158K 1% MK-4 50PPM
R 34,34A,48A	3	42392403	RES. 39.2K 1% MK-3 50PPM
R 37	1	42499303	RES. 4.99K 1% MK-3 50PPM
R 38,63	3	42150403	RES. 15K 1% MK-3 50PPM
R 38A	1	42215503	RES. 215K 1% MK-3 50PPM
R 39	1	42280513	RES. 280K 1% MK-4 50PPM
R 41	1	43100002	RES. 1 OHM 2W 5% W.W.
R 44,45	2	42100703	RES. 10 MEG 1% MK-3 50PPM
R 46	1	43380100	RES. 50 OHM +/-5% 4 1/2W
R 46A	1	43750102	RES. 75 OHM 3W 5%
R 47	1	42768403	RES. 76.8K 1% MK-3 50PPM
R 48B	2	42162503	RES. 162K 1% MK-3 50PPM
R 49	1	42100603	RES. 1 MEG 1% MK-3 50PPM
R 50	1	41100702	RES. 10 MEG 1/4W 5%
R 52	1	42511303	RES. 5.11K 1% MK-3 50PPM
R 53	2	42255403	RES. 25.5K 1% MK-3 50PPM
R 53A,55A	4	42127403	RES. 12.7K 1% MK-3 50PPM
R 54	2	42118403	RES. 11.8K 1% MK-3 50PPM
R 55	2	42536303	RES. 5.36K 1% MK-3 50PPM
R 56,58,59	6	42464303	RES. 4.64K 1% MK-3 50PPM
R 56A	2	42316303	RES. 3.16K 1% MK-3 50PPM
R 57	2	42100314	RES. 1K 1% MK-5 50PPM
R 59A	2	42221303	RES. 2.2K 1% MK-3 50PPM
R 64A	2	42475203	RES. 475 OHM 1% MK-3 50PPM
CONTROLS			
RV 1	1	45100528	100K DUAL GAIN POT
RV 2	1	45100529	100 K DUAL BALANCE POT
RELAYS			
RY 1	2	64101000	RELAY, 12V REED 51P 1200 OHM
SWITCHES			
SW 1,12	2	24100710	TOGGLE SW.,PREM.SILVER,PRE AM
SW 2,3,4,8,9,10	6	24100410	TOGGLE SW.,PREM.GOLD,PRE AMP
SW 5	1	24002100	SWITCH, 5 POS. MODE
SW 6,7,11	3	24002000	SWITCH, 5 POS. ROTARY
TRANSFORMERS			
T 1	1	60007701	XFR. SP9(220/240V) TOROID
INTEGRATED CIRCUITS			
U 1	1	31002200	MC 34071 P MOTOROLA
U 2,3	2	31000801	SP10 TIMER MC1455PI