



Amplifier Current Draw—120 VAC

Current draw is the amount of AC current an amplifier demands while it is operating. Measurements are provided for various loads at idle, 1/8 of average full power, 1/3 of average full power, and full power, with all channels driven simultaneously. The figures shown on this sheet are for 120 VAC usage; for 230- and 100-volt operation, see the companion sheets. For typical usage, use the *idle* and *1/8 power* figures. Where an asterisk (*) appears, the data was not available at press time. The designation "n/a" means "not applicable" to the particular amplifier model.

Model	Idle	1/8 Power				1/3 Power				Full Power			
	Amperes	8Ω	4Ω	2Ω	25V-70V-100V	8Ω	4Ω	2Ω	25V-70V-100V	8Ω	4Ω	2Ω	25V-70V-100V
		Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes
MX700	0.4	2.5	3.8	5.6		2.8	4.5	6.8		6	10	15	
MX1500a	0.9	3.8	4.5	6		6	8	13		12	21	30	
MX2000a	0.9	4.1	7	11		7	10.5	15.5		15	24	40	
MX3000a	1	5.7	8.5	12		10.2	17	24		25	40	58	
USA 400	0.4	2	3	4		2.5	4	5.4		4	7	10	
USA 900	0.6	3.4	5.8	7.4		4	6.3	8.2		10	15	20	
USA 1310	0.9	6	9	13.4		7.5	11.2	15.4		14	21	28	
PL 1.0	0.7	2.8	5.1	7.7		4.5	7.3	11.3		8.2	13.3	20.7	
PL 1.0HV	1	5.1	7.6	nr		6.3	10.8	nr		9.5	17	nr	
PL 1.4	0.8	3.1	5.3	7.2		5.2	8.9	12.3		11.4	18.5	29.4	
PL 1.5x	1.6	3.6	6.4	9.6		6.8	10.8	16.2		12	20	30	
PL 1.6HVx	1.5	5.3	8.5	nr		9.6	15	nr		16.5	28	nr	
PL 1.8	0.8	4.4	7	9.6		7.3	11.5	17.4		15.3	24.9	35.3	
PL 2.0	0.9	6.9	8.7	nr		10.1	14.6	nr		22.9	36	nr	
PL 2.4MB	0.8	5	6.9	11.4		9	12.7	21.2		17.3	26	43	
PL 3.4	0.9	6.9	10.7	13		12.6	17.5	29.7		24.3	37.2	70	
PL 4.0	1	8.1	11.9	15.3		14.5	22.7	33.4		35.8	57.6	83.2	
PL 6.0PFC	2.1	10	16	20		19	31	43		41	72	93	
PL 9.0PFC	2.4	12	19	24		23	38	52		49	87	125	
PLX 1202	0.8	3.8	6	9.6		5.4	8.9	14.3		8.4	14	23	
PLX 1602	0.9	5.6	9	14		8	13.3	21		12.5	21	34	
PLX 2402	0.9	5	7.9	11.8		8.4	13.5	22		15.8	26	42	
PLX 3002	0.9	6	9.5	14		11	17	27		20	33	50	
PLX 3402	0.9	7.6	11.6	16.6		13.1	20	na		25	39	na	
CX 302	0.8	3.8	6	9.6		5.4	8.9	14.3		8.4	14	23	
CX 502	0.9	5.6	9	14		8	13.3	21		12.5	21	34	
CX 702	0.9	5	7.9	11.8		8.4	13.5	22		15.8	26	42	
CX 902	0.9	6	9.5	14		11	17	27		20	33	50	
CX 1102	0.9	7.6	11.6	16.6		13.1	20	na		25	39	na	
CX 302V	0.8				5.7 (70V)				8 (70V)				14 (70V)
CX 602V	0.9				8.7 (70V)				13 (70V)				21 (70V)
CX 1202V	0.9				12 (70V)				19 (70V)				39 (70V)
CX 254	0.7	5.8	9.2	14.3		8.8	14.2	24		14.8	24	38	
CX 404	0.7	8.1	12.4	nr		12.2	19.3	nr		22	33	nr	
CX 204V	0.8				7.7 (70V)				12.1 (70V)				14 (70V)
CX 168	0.6	6.2	9.2			9.2	14.2						
DCA 1222	0.8	3.8	6	9.6		5.4	8.9	14.3		8.4	14	23	
DCA 1622	0.9	5.6	9	14		8	13.3	21		12.5	21	34	
DCA 2422	0.9	5	7.9	11.8		8.4	13.5	22		15.8	26	42	
DCA 3022	0.9	6	9.5	14		11	17	27		20	33	50	
DCA 3422	0.9	7.6	11.6	16.6		13.1	20	na		25	39	na	

DCA 1824		0.7		5.8	9.2	14.3		8.8	14.2	24		14.8	24	38
DCA 1644		0.7		8.1	12.4	nr		12.2	19.3	nr		22	33	nr
PL 218		0.9		5.6	9	14		8	13.3	21		12.5	21	34
PL 224		0.9		5	7.9	11.8		8.4	13.5	22		15.8	26	42
PL 230		0.9		6	9.5	15		11	17	27		20	33	50
PL 236		0.9		7.6	11.6	17		13.1	20	na		25	39	na
RMX 850		0.5		3	4.5	6.5		4.1	6.6	9.5		7.4	11.5	17
RMX 1450		0.5		3.7	6	9.3		5.4	9.6	14.7		10	16	25
RMX 2450		0.6		4	6.3	9.2		9.7	15.6	23		16.4	27	41
Discontinued models														
CX4		0.4		2.3	3.5	4.9		3.4	5.2	7.4		5.7	9.2	13.2
CX6		0.6		3.3	4.8	7.2		4.9	7.4	11		7.7	12.5	18.8
CX12		0.8		4.5	6.1	8		8.4	12.4	16.5		14.7	23	33
CX4T		0.4		2.3	3.5	4.9	3.3	3.4	5.2	7.4	5	5.7	9.2	13.2
CX6T		0.6		3.3	4.8	7.2	4.5	4.9	7.4	11	6.7	7.7	12.5	18.8
CX12T		0.8		4.5	6.1	8	5.7	8.4	12.4	16.5	10.9	14.7	23	33
USA 370		0.4		2	3	4		2.5	4	5.4		4	7	10
USA 850		0.6		3.4	5.8	7.4		4	6.3	8.2		10	15	20
USA 1300		0.9		6	9	13.4		7.5	11.2	15.4		14	21	28
3200		0.4		1.5	2	*		2	3	*		6	8	12
3350		0.4		2.2	3.8	4.4		3	4.5	6.5		9	16	22
3500		1.1		3.3	5	7		4	7	9		11	18	24
3800		0.8		4	6	9		5.5	10	15		12	22	32
SA 185		0.4		2	3	4		2.5	4	5.4		4	7	10
SA 425		0.6		3.4	5.8	7.4		4	6.3	8.2		10	15	20
SA 650		0.9		6	9	13.4		7.5	11.2	15.4		14	21	28
1100		0.1		0.8	1.4	2		1	1.7	2.4		2	3	4
1200		0.4		2	3	4		2.5	4	5.4		4	7	10
1400		0.6		3.4	5.8	7.4		4	6.3	8.2		10	15	20
1700		0.9		6	9	13.4		7.5	11.2	15.4		14	21	28
MPS2300		0.5		2.5	3.2	nr		3.2	4.5	nr		6	7	nr
MX1500		0.4		2.2	3.8	4.4		4	7	9		11	18	24
MX2000		0.8		4	6	9		5.5	10	15		12	22	32
MX1000a		0.4		2.7	4.5	6		3.4	5.5	8.5		8	15	23
EX 800		0.4		2.9	4.5	6.5		4	5.8	8.5		7	11.5	17
EX 1250		0.4		3.5	5.2	7.5		4.5	6.5	9.3		10	15	22
EX 1600		0.5		4.5	7	10.5		7	10.5	15		14.5	22.5	30
EX 2500		1		5	7.5	11		8.6	15	22		19	31	41
EX 4000		1		5.7	8.5	12		10.2	17	24		25	40	58



Amplifier Current Draw—230 VAC

Current draw is the amount of AC current an amplifier demands while it is operating. Measurements are provided for various loads at idle, 1/8 of average full power, 1/3 of average full power, and full power, with all channels driven simultaneously. The figures shown on this sheet are for 230 VAC usage; for 120- and 100-volt operation, see the companion sheets. For typical usage, use the *idle* and *1/8 power* figures. Where an asterisk (*) appears, the data was not available at press time. The designation "n/a" means "not applicable" to the particular amplifier model.

Model	Idle	1/8 Power				1/3 Power				Full Power			
	Amperes	8Ω	4Ω	2Ω	25V-70V-100V	8Ω	4Ω	2Ω	25V-70V-100V	8Ω	4Ω	2Ω	25V-70V-100V
		Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes	Amperes
MX700	0.2	1.25	1.9	2.8		1.4	2.25	3.4		3	5	7.5	
MX1500a	0.45	1.9	2.25	3		3	4	6.5		6	10.5	15	
MX2000a	0.45	2.05	3.5	5.5		3.5	5.25	7.75		7.5	12	20	
MX3000a	0.5	2.85	4.25	6		5.1	8.5	12		12.5	20	29	
USA 400	0.2	1	1.5	2		1.25	2	2.7		2	3.5	5	
USA 900	0.3	1.7	2.9	3.7		2	3.15	4.1		5	7.5	10	
USA 1310	0.45	3	4.5	6.7		3.75	5.6	7.7		7	10.5	14	
PL 1.0	0.35	1.4	2.55	3.85		2.25	3.65	5.65		4.1	6.65	10.35	
PL 1.0HV	0.5	2.55	3.8	nr		3.15	5.4	nr		4.75	8.5	nr	
PL 1.4	0.4	1.55	2.65	3.6		2.6	4.45	6.15		5.7	9.25	14.7	
PL 1.5x	0.8	1.8	3.2	4.8		3.4	5.4	8.1		6	10	15	
PL 1.6HVx	0.75	2.65	4.25	nr		4.8	7.5	nr		8.25	14	nr	
PL 1.8	0.4	2.2	3.5	4.8		3.65	5.75	8.7		7.65	12.45	17.65	
PL 2.0	0.45	3.45	4.35	nr		5.05	7.3	nr		11.45	18	nr	
PL 2.4MB	0.4	2.5	3.45	5.7		4.5	6.35	10.6		8.65	13	21.5	
PL 3.4	0.45	3.45	5.35	6.5		6.3	8.75	14.85		12.15	18.6	35	
PL 4.0	0.5	4.05	5.95	7.65		7.25	11.35	16.7		17.9	28.8	41.6	
PL 6.0PFC	1.05	5	8	10		9.5	15.5	21.5		20.5	36	46.5	
PL 9.0PFC	1.2	6	9.5	12		11.5	19	26		24.5	43.5	62.5	
PLX 1202	0.4	1.9	3	4.8		2.7	4.45	7.15		4.2	7	11.5	
PLX 1602	0.45	2.8	4.5	7		4	6.65	10.5		6.25	10.5	17	
PLX 2402	0.45	2.5	3.95	5.9		4.2	6.75	11		7.9	13	21	
PLX 3002	0.45	3	4.75	7		5.5	8.5	13.5		10	16.5	25	
PLX 3402	0.45	3.8	5.8	8.3		6.55	10	na		12.5	19.5	na	
CX 302	0.4	1.9	3	4.8		2.7	4.45	7.15		4.2	7	11.5	
CX 502	0.45	2.8	4.5	7		4	6.65	10.5		6.25	10.5	17	
CX 702	0.45	2.5	3.95	5.9		4.2	6.75	11		7.9	13	21	
CX 902	0.45	3	4.75	7		5.5	8.5	13.5		10	16.5	25	
CX 1102	0.45	3.8	5.8	8.3		6.55	10	na		12.5	19.5	na	
CX 302V	0.4				2.85 (70V)				4 (70V)				7 (70V)
CX 602V	0.45				4.35 (70V)				6.5 (70V)				10.5 (70V)
CX 1202V	0.45				6 (70V)				9.5 (70V)				19.5 (70V)
CX 254	0.35	2.9	4.6	7.15		4.4	7.1	12		7.4	12	19	
CX 404	0.35	4.05	6.2	nr		6.1	9.65	nr		11	16.5	nr	
CX 204V	0.4				3.85 (70V)				6.05 (70V)				7 (70V)
CX 168	0.3	3.1	4.6			4.6	7.1						
DCA 1222	0.4	1.9	3	4.8		2.7	4.45	7.15		4.2	7	11.5	
DCA 1622	0.45	2.8	4.5	7		4	6.65	10.5		6.25	10.5	17	
DCA 2422	0.45	2.5	3.95	5.9		4.2	6.75	11		7.9	13	21	
DCA 3022	0.45	3	4.75	7		5.5	8.5	13.5		10	16.5	25	
DCA 3422	0.45	3.8	5.8	8.3		6.55	10	na		12.5	19.5	na	

DCA 1824		0.35		2.9	4.6	7.15		4.4	7.1	12		7.4	12	19
DCA 1644		0.35		4.05	6.2	nr		6.1	9.65	nr		11	16.5	nr
PL 218		0.45		2.8	4.5	7		4	6.65	10.5		6.25	10.5	17
PL 224		0.45		2.5	3.95	5.9		4.2	6.75	11		7.9	13	21
PL 230		0.45		3	4.75	7.5		5.5	8.5	13.5		10	16.5	25
PL 236		0.45		3.8	5.8	8.5		6.55	10	na		12.5	19.5	na
RMX 850		0.25		1.5	2.25	3.25		2.05	3.3	4.75		3.7	5.75	8.5
RMX 1450		0.25		1.85	3	4.65		2.7	4.8	7.35		5	8	12.5
RMX 2450		0.3		2	3.15	4.6		4.85	7.8	11.5		8.2	13.5	20.5
Discontinued models														
CX4		0.2		1.15	1.75	2.45		1.7	2.6	3.7		2.85	4.6	6.6
CX6		0.3		1.65	2.4	3.6		2.45	3.7	5.5		3.85	6.25	9.4
CX12		0.4		2.25	3.05	4		4.2	6.2	8.25		7.35	11.5	16.5
CX4T		0.2		1.15	1.75	2.45	1.65	1.7	2.6	3.7	2.5	2.85	4.6	6.6
CX6T		0.3		1.65	2.4	3.6	2.25	2.45	3.7	5.5	3.35	3.85	6.25	9.4
CX12T		0.4		2.25	3.05	4	2.85	4.2	6.2	8.25	5.45	7.35	11.5	16.5
USA 370		0.2		1	1.5	2		1.25	2	2.7		2	3.5	5
USA 850		0.3		1.7	2.9	3.7		2	3.15	4.1		5	7.5	10
USA 1300		0.45		3	4.5	6.7		3.75	5.6	7.7		7	10.5	14
3200		0.2		0.75	1	*		1	1.5	*		3	4	6
3350		0.2		1.1	1.9	2.2		1.5	2.25	3.25		4.5	8	11
3500		0.55		1.65	2.5	3.5		2	3.5	4.5		5.5	9	12
3800		0.4		2	3	4.5		2.75	5	7.5		6	11	16
SA 185		0.2		1	1.5	2		1.25	2	2.7		2	3.5	5
SA 425		0.3		1.7	2.9	3.7		2	3.15	4.1		5	7.5	10
SA 650		0.45		3	4.5	6.7		3.75	5.6	7.7		7	10.5	14
1100		0.05		0.4	0.7	1		0.5	0.85	1.2		1	1.5	2
1200		0.2		1	1.5	2		1.25	2	2.7		2	3.5	5
1400		0.3		1.7	2.9	3.7		2	3.15	4.1		5	7.5	10
1700		0.45		3	4.5	6.7		3.75	5.6	7.7		7	10.5	14
MPS2300		0.25		1.25	1.6	nr		1.6	2.25	nr		3	3.5	nr
MX1500		0.2		1.1	1.9	2.2		2	3.5	4.5		5.5	9	12
MX2000		0.4		2	3	4.5		2.75	5	7.5		6	11	16
MX1000a		0.2		1.35	2.25	3		1.7	2.75	4.25		4	7.5	11.5
EX 800		0.2		1.45	2.25	3.25		2	2.9	4.25		3.5	5.75	8.5
EX 1250		0.2		1.75	2.6	3.75		2.25	3.25	4.65		5	7.5	11
EX 1600		0.25		2.25	3.5	5.25		3.5	5.25	7.5		7.25	11.25	15
EX 2500		0.5		2.5	3.75	5.5		4.3	7.5	11		9.5	15.5	20.5
EX 4000		0.5		2.85	4.25	6		5.1	8.5	12		12.5	20	29



Amplifier Current Draw—100 VAC

Current draw is the amount of AC current an amplifier demands while it is operating. Measurements are provided for various loads at idle, 1/8 of average full power, 1/3 of average full power, and full power, with all channels driven simultaneously. The figures shown on this sheet are for 100 VAC usage; for 230- and 120-volt operation, see the companion sheets. For typical usage, use the *idle* and *1/8 power* figures. Where an asterisk (*) appears, the data was not available at press time. The designation "n/a" means "not applicable" to the particular amplifier model.

Model	Idle	1/8 Power				1/3 Power				Full Power			
	Amperes	8Ω Amperes	4Ω Amperes	2Ω Amperes	25V-70V-100V Amperes	8Ω Amperes	4Ω Amperes	2Ω Amperes	25V-70V-100V Amperes	8Ω Amperes	4Ω Amperes	2Ω Amperes	25V-70V-100V Amperes
MX700	0.48	3	4.56	6.72		3.36	5.4	8.16		7.2	12	18	
MX1500a	1.08	4.56	5.4	7.2		7.2	9.6	15.6		14.4	25.2	36	
MX2000a	1.08	4.92	8.4	13.2		8.4	12.6	18.6		18	28.8	48	
MX3000a	1.2	6.84	10.2	14.4		12.24	20.4	28.8		30	48	69.6	
USA 400	0.48	2.4	3.6	4.8		3	4.8	6.48		4.8	8.4	12	
USA 900	0.72	4.08	6.96	8.88		4.8	7.56	9.84		12	18	24	
USA 1310	1.08	7.2	10.8	16.08		9	13.44	18.48		16.8	25.2	33.6	
PL 1.0	0.84	3.36	6.12	9.24		5.4	8.76	13.56		9.84	15.96	24.84	
PL 1.0HV	1.2	6.12	9.12	nr		7.56	12.96	nr		11.4	20.4	nr	
PL 1.4	0.96	3.72	6.36	8.64		6.24	10.68	14.76		13.68	22.2	35.28	
PL 1.5x	1.92	4.32	7.68	11.52		8.16	12.96	19.44		14.4	24	36	
PL 1.6HVx	1.8	6.36	10.2	nr		11.52	18	nr		19.8	33.6	nr	
PL 1.8	0.96	5.28	8.4	11.52		8.76	13.8	20.88		18.36	29.88	42.36	
PL 2.0	1.08	8.28	10.44	nr		12.12	17.52	nr		27.48	43.2	nr	
PL 2.4MB	0.96	6	8.28	13.68		10.8	15.24	25.44		20.76	31.2	51.6	
PL 3.4	1.08	8.28	12.84	15.6		15.12	21	35.64		29.16	44.64	84	
PL 4.0	1.2	9.72	14.28	18.36		17.4	27.24	40.08		42.96	69.12	99.84	
PL 6.0PFC	2.52	12	19.2	24		22.8	37.2	51.6		49.2	86.4	111.6	
PL 9.0PFC	2.88	14.4	22.8	28.8		27.6	45.6	62.4		58.8	104.4	150	
PLX 1202	0.96	4.56	7.2	11.52		6.48	10.68	17.16		10.08	16.8	27.6	
PLX 1602	1.08	6.72	10.8	16.8		9.6	15.96	25.2		15	25.2	40.8	
PLX 2402	1.08	6	9.48	14.16		10.08	16.2	26.4		18.96	31.2	50.4	
PLX 3002	1.08	7.2	11.4	16.8		13.2	20.4	32.4		24	39.6	60	
PLX 3402	1.08	9.12	13.92	19.92		15.72	24	na		30	46.8	na	
CX 302	0.96	4.56	7.2	11.52		6.48	10.68	17.16		10.08	16.8	27.6	
CX 502	1.08	6.72	10.8	16.8		9.6	15.96	25.2		15	25.2	40.8	
CX 702	1.08	6	9.48	14.16		10.08	16.2	26.4		18.96	31.2	50.4	
CX 902	1.08	7.2	11.4	16.8		13.2	20.4	32.4		24	39.6	60	
CX 1102	1.08	9.12	13.92	19.92		15.72	24	na		30	46.8	na	
CX 302V	0.96				6.84 (70V)				9.6 (70V)				16.8 (70V)
CX 602V	1.08				10.44 (70V)				15.6 (70V)				25.2 (70V)
CX 1202V	1.08				14.4 (70V)				22.8 (70V)				46.8 (70V)
CX 254	0.84	6.96	11.04	17.16		10.56	17.04	28.8		17.76	28.8	45.6	
CX 404	0.84	9.72	14.88	nr		14.64	23.16	nr		26.4	39.6	nr	
CX 204V	0.96				9.24 (70V)				14.5 (70V)				16.8 (70V)
CX 168	0.72	7.44	11.04			11.04	17.04						
DCA 1222	0.96	4.56	7.2	11.52		6.48	10.68	17.16		10.08	16.8	27.6	
DCA 1622	1.08	6.72	10.8	16.8		9.6	15.96	25.2		15	25.2	40.8	
DCA 2422	1.08	6	9.48	14.16		10.08	16.2	26.4		18.96	31.2	50.4	
DCA 3022	1.08	7.2	11.4	16.8		13.2	20.4	32.4		24	39.6	60	
DCA 3422	1.08	9.12	13.92	19.92		15.72	24	na		30	46.8	na	

DCA 1824		0.84		6.96	11.04	17.16		10.56	17.04	28.8		17.76	28.8	45.6
DCA 1644		0.84		9.72	14.88	nr		14.64	23.16	nr		26.4	39.6	nr
PL 218		1.08		6.72	10.8	16.8		9.6	15.96	25.2		15	25.2	40.8
PL 224		1.08		6	9.48	14.16		10.08	16.2	26.4		18.96	31.2	50.4
PL 230		1.08		7.2	11.4	18		13.2	20.4	32.4		24	39.6	60
PL 236		1.08		9.12	13.92	20.4		15.72	24	na		30	46.8	na
RMX 850		0.6		3.6	5.4	7.8		4.92	7.92	11.4		8.88	13.8	20.4
RMX 1450		0.6		4.44	7.2	11.16		6.48	11.52	17.64		12	19.2	30
RMX 2450		0.72		4.8	7.56	11.04		11.64	18.72	27.6		19.68	32.4	49.2
Discontinued models														
CX4		0.48		2.76	4.2	5.88		4.08	6.24	8.88		6.84	11.04	15.84
CX6		0.72		3.96	5.76	8.64		5.88	8.88	13.2		9.24	15	22.56
CX12		0.96		5.4	7.32	9.6		10.08	14.88	19.8		17.64	27.6	39.6
CX4T		0.48		2.76	4.2	5.88	3.96	4.08	6.24	8.88	6	6.84	11.04	15.84
CX6T		0.72		3.96	5.76	8.64	5.4	5.88	8.88	13.2	8.04	9.24	15	22.56
CX12T		0.96		5.4	7.32	9.6	6.84	10.08	14.88	19.8	13.08	17.64	27.6	39.6
USA 370		0.48		2.4	3.6	4.8		3	4.8	6.48		4.8	8.4	12
USA 850		0.72		4.08	6.96	8.88		4.8	7.56	9.84		12	18	24
USA 1300		1.08		7.2	10.8	16.08		9	13.44	18.48		16.8	25.2	33.6
3200		0.48		1.8	2.4	*		2.4	3.6	*		7.2	9.6	14.4
3350		0.48		2.64	4.56	5.28		3.6	5.4	7.8		10.8	19.2	26.4
3500		1.32		3.96	6	8.4		4.8	8.4	10.8		13.2	21.6	28.8
3800		0.96		4.8	7.2	10.8		6.6	12	18		14.4	26.4	38.4
SA 185		0.48		2.4	3.6	4.8		3	4.8	6.48		4.8	8.4	12
SA 425		0.72		4.08	6.96	8.88		4.8	7.56	9.84		12	18	24
SA 650		1.08		7.2	10.8	16.08		9	13.44	18.48		16.8	25.2	33.6
1100		0.12		0.96	1.68	2.4		1.2	2.04	2.88		2.4	3.6	4.8
1200		0.48		2.4	3.6	4.8		3	4.8	6.48		4.8	8.4	12
1400		0.72		4.08	6.96	8.88		4.8	7.56	9.84		12	18	24
1700		1.08		7.2	10.8	16.08		9	13.44	18.48		16.8	25.2	33.6
MPS2300		0.6		3	3.84	nr		3.84	5.4	nr		7.2	8.4	nr
MX1500		0.48		2.64	4.56	5.28		4.8	8.4	10.8		13.2	21.6	28.8
MX2000		0.96		4.8	7.2	10.8		6.6	12	18		14.4	26.4	38.4
MX1000a		0.48		3.24	5.4	7.2		4.08	6.6	10.2		9.6	18	27.6
EX 800		0.48		3.48	5.4	7.8		4.8	6.96	10.2		8.4	13.8	20.4
EX 1250		0.48		4.2	6.24	9		5.4	7.8	11.16		12	18	26.4
EX 1600		0.6		5.4	8.4	12.6		8.4	12.6	18		17.4	27	36
EX 2500		1.2		6	9	13.2		10.32	18	26.4		22.8	37.2	49.2
EX 4000		1.2		6.84	10.2	14.4		12.24	20.4	28.8		30	48	69.6