

Service Manual

PM6010K/N1B/T1B
/N1G/T1G

Integrated Amplifier



PM6010 KI

REMARK : This service manual explains the differences between the PM6010F/N1B/T1G/N1G/T1G (OSE version) and the PM6010K/N1B/T1G/N1G/T1G (KI version). Only the electrical differences are listed. The mechanical parts, which differ, are not available as spare part.

All other information is described in the service manual of the model PM6010F/N1B/T1G/N1G/T1G (Code number : **3120 785 22009**). The dispatch of the parts for after sales service has to be referred to this service manual, with the first priority.

For this reason, please use this service manual with referring to the model PM6010F service manual without fail.

PM6010KI is equal to the PM6010OSE except the following electrical changes (mechanical changes are not listed):

Position No.	Service code	Description
L001	4822 146 10788	Transformer 230V
F902		Fuse 2.5AT
C703, C704	-	Removed
C707, C708	9965 000 08133	330pF Styrene
C713, C714	9965 000 08134	10pF Styrene
C717,C718	9965 000 08135	47uF 50V Silmic
C720	4822 124 22039	220uF 16V Cerafine
C753, C754, C755, C756	9965 000 08136	120pF Styrene
C801x, C802x Note: These are added in parallel to C801/C802	9965 000 08137	1000uF 50V Silmic
C471,C472	4822 124 80119	100uF Silmic 25V
C455, C456, C467, C468	4822 124 80543	10uF 35V Silmic

marantz®

PM6010 KI