

Project 61 BlamelessAmp BOM R2			
Item	Part Id	Part Value	Part Description
1	C1	47uF 25V	47uF 25V electrolytic capacitor
2	C2	220pF 100V	220pF 100V multilayer ceramic capacitor
3	C3	0.22uF 63V	0.22uF 63V film capacitor
4	C4	47uF 25V	47uF 25V electrolytic capacitor
5	C5	1000uF16V	1000uF 16V electrolytic capacitor
6	C6	47uF 25V	47uF 25V electrolytic capacitor
7	C7	0.1uF 100V	0.1uF 100V multilayer ceramic capacitor
8	C8	100pF 100V	100pF 100V multilayer ceramic capacitor
9	C9	0.1uF 100V	0.1uF 100V film capacitor
10	C10	220pF 100V	220pF 100V multilayer ceramic capacitor
11	C11	470uF 63V	470uF 63V electrolytic capacitor
12	C12	47uF 25V	47uF 25V electrolytic capacitor
13	C13	Not populated	Not populated
14	C14	0.22uF 63V	0.22uF 63V film capacitor
15	C15	680uF 80V	680uF 80V electrolytic capacitor
16	C16	0.1uF 250VAC	0.1uF 250VAC film capacitor
17	C17	680uF 80V	680uF 80V electrolytic capacitor
18	D1	1N4148	1N4148
19	D2	1N4148	1N4148
20	D3	1N4007	1N4007
21	D4	1N4007	1N4007
22	F+	5A 250V	5A 250V 5x20mm fuse
23	F-	5A 250V	5A 250V 5x20mm fuse
24	J1	640456-2	640456-2 Tyco 2P header
25	L1	see "How-to"	see "How-to"
26	Q1	2SA992	2SA992
27	Q2	2SA992	2SA992
28	Q3	2SC1845	2SC1845
29	Q4	2SC1845	2SC1845
30	Q5	2SA992	2SA992
31	Q6	2SA992	2SA992
32	Q7	2SC1845	2SC1845
33	Q8	2SA1381	2SA1381
34	Q9	2SC3503	2SC3503
35	Q10	2SC4793	2SC4793
36	Q11	2SA1837	2SA1837
37	Q12	2SA1962	2SA1962
38	Q13	2SA1962	2SA1962
39	Q14	2SC5242	2SC5242
40	Q15	2SC5242	2SC5242
41	Q16	2SC3503	2SC3503
42	R1	100K 1/4W	100K 1/4W metal film resistor
43	R2	12K 1/4W	12K 1/4W metal film resistor
44	R3	100 1/4W	100 1/4W metal film resistor
45	R4	100 1/4W	100 1/4W metal film resistor
46	R5	68 1/4W	68 1/4W metal film resistor
47	R6	100 1/4W	100 1/4W metal film resistor
48	R7	2.2K 1/4W	2.2K 1/4W metal film resistor
49	R8	100 1/4W	100 1/4W metal film resistor
50	R9	68 1/4W	68 1/4W metal film resistor
51	R10	2.2K 1/4W	2.2K 1/4W metal film resistor
52	R11	270 1/4W	270 1/4W metal film resistor
53	R12	12K 1/4W	12K 1/4W metal film resistor
54	R13	10K 1/4W	10K 1/4W metal film resistor
55	R14	2.2K 1/4W	2.2K 1/4W metal film resistor
56	R15	Not populated	Not populated
57	R16	2.2K 1/4W	2.2K 1/4W metal film resistor
58	R17	1K 1/4W	1K 1/4W metal film resistor
59	R18	220 1/4W	220 1/4W metal film resistor
60	R19	68 1/4W	68 1/4W metal film resistor
61	R20	15 1/4W	15 1/4W metal film resistor
62	R21	100 1/4W	100 1/4W metal film resistor
63	R22	100 1/4W	100 1/4W metal film resistor
64	R23	10K 1/4W	10K 1/4W metal film resistor
65	R24	Not populated	Not populated
66	R25	100 1/2W	100 1/2W metal film resistor
67	R26	100 1/2W	100 1/2W metal film resistor
68	R27	4.7 1/4W	4.7 1/4W metal film resistor
69	R28	4.7 1/4W	4.7 1/4W metal film resistor
70	R29	4.7 1/4W	4.7 1/4W metal film resistor
71	R30	4.7 1/4W	4.7 1/4W metal film resistor
72	R31	0.22 5W	0.22 5W radial wirewound resistor
73	R32	0.22 5W	0.22 5W radial wirewound resistor
74	R33	0.22 5W	0.22 5W radial wirewound resistor
75	R34	0.22 5W	0.22 5W radial wirewound resistor
76	R35	10 2W	10 2W metal film resistor
77	R36	4.7 2W	4.7 2W SMT metal film resistor
78	R37	2K 1/4W	2K 1/4W metal film resistor
79	R38	10 1W	10 1W metal film resistor
80	R39	0 1/4W	0 1/4W Link metal film resistor
81	R40	0 1/4W	0 1/4W Link metal film resistor
82	R41	0 1/4W	0 1/4W Link metal film resistor
83	R42	0 1/4W	0 1/4W Link metal film resistor
84	R43	0 1/4W	0 1/4W Link metal film resistor
85	VR1	2K trimpot	2K multiturn trimpot